



**INPUT SPECIFICATIONS**

Voltage	115/230 V Auto Range, ± 15 % Variation
Frequency	50/60 Hz ± 5%
Fuse	115 VAC, 230 VAC – 10 A Slow Blow 250 VAC

**DIELECTRIC WITHSTAND TEST MODE**

Output Rating	5 kV @ 50 mAAC 5 kV @ 100 mAAC (Models 825X) 6 kV @ 20 mADC		
Voltage Setting	Resolution:	1 V	
	Accuracy:	± (1.5% of setting + 5 volts)	
HI and LO-Limit	AC Total	Range:	0.000 – 9.999 mA
		Resolution:	0.001 mA
		Accuracy:	± (2% of setting + 2 counts)
	AC Real	Range:	10.00 – 50.00 mA (100.00 mA, models 825X)
		Resolution:	0.01 mA
		Accuracy:	± (2% of setting + 2 counts)
DC	Range:	0 – 999.9 µA	
	Resolution:	0.1 µA	
	Accuracy:	± (2% of setting + 2 counts)	

Arc Detection	Range:	1 – 9 (9 is most sensitive)
---------------	--------	-----------------------------

Ground Continuity	Current: DC 0.1 A ± 0.01 A, fixed Max. Ground Resistance: 1 Ω ± 0.1 Ω, fixed
-------------------	---

Ground Fault Interrupt	GFI Trip Current: 0.4 mA – 5.0 mA (AC or DC) HV Shut Down Speed: < 1 ms
------------------------	--

DC Output Ripple	≤ 4% Ripple rms at 5 kVDC at 20 mA Resistive Load
------------------	---

Discharge Time	≤ 50 ms No Load, < 100 ms for Capacitive Load
----------------	---

Max Capacitive Load, DC Mode	1 µF < 1 kV	0.08 µF < 4 kV
	0.75 µF < 2 kV	0.04 µF < 6 kV
	0.5 µF < 3 kV	

AC Output Waveform	Sine Wave, Crest Factor = 1.3 – 1.5
--------------------	-------------------------------------

Output Frequency	Range:	60 or 50 Hz, User Selection (400/800 Hz optional)
------------------	--------	---

Output Regulation	± (1% of output + 5 V) from no load to full load and over input voltage range
-------------------	---

Dwell Timer	Range:	AC 0.4 – 999.9 sec (0=Continuous)
	Range:	DC 0.3 – 999.9 sec (0=Continuous)

Ramp Timer	Ramp-up:	AC 0.1 – 999.9 sec, DC 0.4 – 999.9 sec
	Ramp-Down:	AC 0.0 – 999.9 sec, DC 0.0, 1.0 – 999.9 sec (0=Continuous)
	Down:	(0=Continuous)

**INSULATION RESISTANCE TEST MODE**

Voltage Setting	Range:	30 – 6000 VDC
-----------------	--------	---------------

HI and LO-Limit	Range:	0.05 MΩ – 99.99 MΩ
	Resolution:	0.01 MΩ
	Range:	100.0 MΩ – 999.9 MΩ
	Resolution:	0.1 MΩ
	Range:	1,000 MΩ – 50,000 MΩ
	Resolution:	1 MΩ (HI-Limit: 0=OFF)

Ramp Timer	Ramp-up:	0.1 – 999.9 sec
	Ramp-Down:	0.0, 1.0 – 999.9 sec (0=Continuous)
	Down:	(0=Continuous)

Delay Timer	Range:	0.5 – 999.9 sec (0=Continuous)
-------------	--------	--------------------------------

**GROUND BOND TEST MODE**

Output Voltage (Open Circuit Limit)	Range:	3.00 – 8.00 VAC
-------------------------------------	--------	-----------------

Output Frequency	Range:	60 or 50 Hz, User Selectable
------------------	--------	------------------------------

Output Current	Range:	1.00 – 40.00 A
	Resolution:	0.01 A
	Accuracy:	± (2% of setting + 0.02 A)

Maximum Loading	1.00 – 10.00 A,	0 – 600 mΩ
	10.01 – 30.00 A,	0 – 200 mΩ
	30.01 – 40.00 A,	0 – 150 mΩ

HI and LO-Limit	Range:	0 – 150 mΩ for 30.01 – 40.00 A
	Resolution:	0 – 200 mΩ for 10.01 – 30.00 A
	Accuracy:	0 – 600 mΩ for 1.00 – 10.00 A
	Resolution:	1 mΩ
	Accuracy:	± (2% of reading + 2 mΩ)

	Range:	0 – 600 mΩ for 1.00 – 5.99 A
	Resolution:	1 mΩ
	Accuracy:	± (3% of reading + 3 mΩ)

Dwell Timer	Range:	0.5 – 999.9 sec (0=Continuous)
-------------	--------	--------------------------------

Milliohm Offset	Range:	0 – 200 mΩ
-----------------	--------	------------

**CONTINUITY TEST MODE**

Output Current	DC 0.01 A ± 0.00001 A
----------------	-----------------------

Resistance Display	Range:	0.00 – 10000 Ω
--------------------	--------	----------------

HI and LO-Limit	Range:	1: 0.00 – 10.00 Ω
	Resolution:	0.01 Ω
	Range 2:	10.1 – 100.0 Ω
	Resolution:	0.1 Ω

	Range 3:	101 – 1,000 Ω
	Resolution:	1 Ω
	Accuracy:	± (1% of reading + 3 counts)

	Range 4:	1,001 – 10,000 Ω
	Resolution:	1 Ω
	Accuracy:	± (1% of reading + 10 counts) (Max Limit: 0=OFF)

Dwell Timer	Range:	0.0, 0.3 – 999.9 sec (0=Continuous)
-------------	--------	-------------------------------------

Milliohm Offset	Range:	0.00 – 10.00 Ω
-----------------	--------	----------------

**RUN TEST MODE (Models 82X6 & 82X7 only)**

DUT Power	Voltage:	0 – 277 VAC single phase unbalanced
	Current:	16 AAC max continuous
	Range:	0.0 – 277.0 VAC Full Scale
	Resolution:	0.1 V
	Accuracy:	± (1.5% of reading + 0.2 V), 30.0 – 277.0 VAC
		Short Circuit Protection: 23 AAC, Response Time < 3 sec

Delay Time Setting	Range:	0.2 – 999.9 seconds
--------------------	--------	---------------------

Dwell Time Setting	Range:	0.1 – 999.9 seconds (0=Continuous)
--------------------	--------	------------------------------------

# OMNIA® II Series

RUN TEST MODE CONTINUED (Models 82X6 & 82X7 only)		
Trip Point Settings & Metering	<b>Voltage</b>	
	Volt-Hi Volt-LO	Range: 30.0 – 277.0 VAC Resolution: 0.1 V Accuracy: ± (1.5% of setting + 0.2 V), 30.0–277 VAC
	<b>Current</b>	
	Amp-HI Amp-LO	Range: 0.0 – 16.00 AAC Resolution: 0.01 A Accuracy: ± (2.0% of setting + 2 counts)
	<b>Watts</b>	
	Power-HI Power-LO	Range: 0 – 4,500 W Resolution: 1 W Accuracy: ± (5.0% of setting + 3 counts)
	<b>Power Factor</b>	
PF-HI PF-LO	Range: 0.000 – 1.000 Resolution: 0.001 Accuracy: ± (8% of setting + 2 counts)	
<b>Leakage Current</b>		
Leak-HI Leak-LO	Range: 0.00 – 10.00 mA (0=OFF) Resolution: 0.01 mA Accuracy: ± (2% of setting + 2 counts)	
Timer Display	Range: 0.0 – 999.9 seconds Resolution: 0.1 second Accuracy: ± (0.1% of reading + 0.05 seconds)	
LEAKAGE CURRENT TEST MODE (Models 82X6 & 82X7 only)		
DUT Power	Voltage: Current:	0 – 277 VAC 16 AAC max continuous
	Voltage Display	Range: 0.0 – 277.0 VAC Full Scale Resolution: 0.1 V Accuracy: ± (1.5% of reading +0.2 V), 30.0 – 277.0 VAC
	Short Circuit Protection:	23 AAC, Response Time < 3 s
Reverse Power Switch	Reverse polarity switch setting select ON/OFF/AUTO ON: Reverse power OFF: Normal AUTO: Automatic Reverse Polarity	
Neutral Switch	ON/OFF selection for single fault condition	
Ground Switch	ON/OFF selection for Class I single fault condition	
Probe Setting	Surface to Surface (PH – PL) Surface to Line (PH – L) Ground to Line (G – L)	
Touch Current High Limit (rms)	Range: Resolution:	0.0 µA ~ 999.9 µA 1000 µA ~ 10.00 mA 0.1 µA / 1 µA / 0.01 mA

LEAKAGE CURRENT TEST MODE CONTINUED (Models 82X6 & 82X7 only)	
Touch Current Display (rms)	Range 1: 0.0 µA ~ 32.0 µA, frequency DC, 15 Hz – 1 MHz
	Range 2: 28.0 µA ~ 130.0 µA, frequency DC, 15 Hz – 1 MHz
	Range 3: 120.0 µA ~ 550.0 µA, frequency DC, 15 Hz – 1 MHz
	Resolution for Ranges 1, 2, 3: 0.1 µA
	Accuracy for Ranges 1, 2, 3: DC: 15 Hz < f < 100 KHz: ± (2% of reading + 3 counts) 100 KHz < f < 1 MHz: ± 5% of reading (10.0 µA – 999.9 µA)
	Range 4: 400 µA ~ 2100 µA, frequency DC, 15 Hz – 1 MHz
	Range 5: 800 µA ~ 8500 µA, frequency DC, 15 Hz – 1 MHz
	Resolution for Ranges 4 & 5: 1 µA
	Accuracy for Ranges 4 & 5: DC: 15 Hz < f < 100 KHz: ± (2% of reading + 3 counts) 100 KHz < f < 1 MHz: ± 5% of reading (10 µA – 8500 µA)
	Range 6: 8.00 mA ~ 10.00 mA, frequency DC 15 Hz – 100 kHz
Resolution: 0.01 mA	
Accuracy: DC: 15 Hz < f < 100 KHz: ± 5% of reading (0.01 mA -10.00 mA)	
Touch Current Display (Peak)	Range 1: 0.0 µA ~ 32.0 µA, frequency DC – 1 MHz
	Range 2: 28.0 µA ~ 130.0 µA, frequency DC – 1 MHz
	Range 3: 120.0 µA ~ 550.0 µA, frequency DC – 1 MHz
	Resolution for Ranges 1, 2, 3: 0.1 µA
	Accuracy for Ranges 1, 2, 3: DC: ± (2% of reading + 2 µA) 15 Hz < f < 1 MHz: ± 10% of reading + 2 µA
	Range 4: 400 µA ~ 2100 µA, frequency DC – 1 MHz
	Range 5: 1800 A ~ 8500 µA, frequency DC – 1 MHz
	Resolution for Ranges 4 & 5: 1 µA
	Accuracy for Ranges 4 & 5: DC: ± (2% of reading + 2 µA) 15 Hz < f < 1 MHz: ±(10% of reading + 2 µA)
	Range 6: 8.0 mA ~10.00 mA, frequency DC – 100 KHz
Resolution: 0.01 mA	
Accuracy: DC: ± (2% of reading + 3 counts) 15 Hz < f < 100 KHz: ± (10% of reading + 2 counts)	
MD Circuit Module	MD1: UL544NP, UL484 , UL923, UL471, UL867, UL697
	MD2: UL544P
	MD3: IEC 60601-1
	MD4: UL1563
	MD5: IEC60990 Fig4 U2, IEC62368-1, IEC60335-1, IEC60598-1, IEC60065, IEC61010
	MD6: IEC60990 Fig5 U3, IEC60598-1
	MD7: IEC62368-1, IEC61010-1 FigA.2 (2K ohm) for Run function
	MD8: IEC60990/IEC62368-1 Fig4 U1
External MD	Basic measuring element 1 kΩ
Scope Output Interface	BNC type connector on rear panel for Oscilloscope connection

AC POWER SOURCE (82X7 only)	
Output	Power: 630 VA and 500 W Maximum
	Voltage: 0 – 150.0 V / 0 – 277.0 V
	Current: 4.20 A maximum for 0 – 150 V range 2.10 A maximum 0 – 277 V range
	Distortion: ≤ 1% at 45- 500 Hz and output voltage within the 80 ~ 140 VAC at Low Range or the 160 ~ 277 VAC at High Range (Resistive Load)
	Regulation: ≤ 0.5% + 5 V (resistive load), from no load to full load and Low Line to High Line (combined regulation)
	Crest Factor: > 3
	Test Timing: < 350 ms at start and between
	Limit: Steps when internal AC source is ON
Settings	Voltage
	Low Range: 0.0 – 150.0 V
	High Range: 0.0 – 277.0 V
	Resolution: 0.1 V
	Accuracy: ± (1.5% of setting + 2 counts)
	Frequency
Range: 45.0 Hz – 99.9 Hz	
Resolution: 0.1 Hz	
Accuracy: ± 0.1% of setting	
Range: 100 Hz – 500 Hz	
Resolution: 1 Hz	
Accuracy: ± 0.1% of setting	
A-HI-Limit	
Range: 4.20 A / 2.10 A	
Resolution: 0.01 A	
Accuracy: ± (2% of reading + 2 counts)	
Measurement	Voltage
	Range: 0.0 – 277.0 V
	Resolution: 0.1 V
	Accuracy: ± (1.5% of reading + 2 counts)
	Current
	Range: 0.00 – 16.00 A
Resolution: 0.01 A	
Accuracy: ± (2% of reading + 2 counts)	
Power	
Range: 0 – 4500	
Resolution: 1	
Accuracy: ± (5% of reading + 3 counts) for PF > 0.100	
Power Factor	
Range: 0.000 – 1.000	
Resolution: 0.001	
Accuracy: ± (8% of reading + 5 counts)	
Frequency	
Range: 45 – 500 Hz	
Resolution: 0.1 Hz	
Accuracy: ± 0.1 Hz	

GENERAL SPECIFICATIONS	
PLC Remote Control	Input: Test, Reset, Interlock, Recall File 1 through 3 Output: Pass, Fail, Test-in-Process
Safety	Built-in SmartGFI circuit
Memory	10,000 Steps
Interface	Standard: USB/RS-232 Optional: Ethernet or GPIB
Security	Advanced security system with access levels and username/password requirements
Dimensions (W x H x D)	16.93" x 5.24" x 19.69" (430 x 133 x 500 mm)
Weight	8204: 82 lbs (37 kg) 8254: 92 lbs (42 kg) 8206/8207: 83 lbs (38 kg) 8256/8257: 103 lbs (47 kg)

For reading specifications, please refer to the user manual.

**Why We Use Counts**

Associated Research publishes some specifications using “counts” which allows us to provide a better indication of the instrument’s capabilities across measurement ranges. A count refers to the lowest resolution of the display for a given measurement range. For example, if the resolution for voltage is 1V then 2 counts = 2 V.

The default of the Adapter Box accessory come in L-N polarity. N-L polarity is available upon request.

Specifications subject to change without notice.